



40XX SERIES

Advanced Purification System

4005, 4007 & 4030 Purifier Models



- Plug and play installation and activation
- Ultra-Low Energy efficiency <math>< 0.65\text{Amps}</math> (78.0w 120V 1PH)
- Touch screen controller
- Dynamic monitoring control with internal/external controller and sensor
- Easy maintenance
- Logging available for reporting
- Portable Option

How it Works:

**Existing Air
(Containing Microorganisms)**



**ROS
(Reactive Oxygen Species)**



AirROS purifiers utilize electricity and create ROS. The highly-reactive ROS inside the purifier DESTROYS Molds, Pathogens, Viruses, and Odors as they pass through the chamber.

The sanitized air that comes out of the purifier enters the environment and continues to sanitize ALL surfaces it contacts.

40XX Series Surface & Air Purifiers will sanitize indoor air & surfaces in rooms 550-30,000 cubic feet using less than 0.70Amps (78.0 watts)

► Model Number

- 4005 5,500 ft³ *
- 4007 7,500 ft³ *
- 4030 30,000 ft³ *
- C Controller - Touch Screen Controller
- S Sensor - Ozone †
- P Portable - Handle/feet
- I Internal Controller option
- T Transparent Controller Lid w/ SS Latch
- R Remote Sensor option

† Internal or External sensor required for dynamic control
 * Actual Capacity depends on Oxygen level, Temp, and Commodity factors

► Benefits:

- Destroys Mold, Bacteria, Yeast, Pathogens, & Viruses
- Eliminates/neutralizes Odor
- Organic no-chemicals added
- Reduces cross-contamination
- Ultra-low power consumption

Example Configurations:

4005CS
 4007C-P
 4030/4000CSI
 4030/4000CIT/4000S

Standard Wall mount
 3inch (3.5"OD) PVC Sch40 Output



40XX



40XX-P



40XXC



40XXC-P



40XXCS



40XXCS-P



4000CSI
 4000S



4000CITR

40XX SERIES

Model	Capacity ft ³	Dimensions	(-P) Portable Dimensions	Amps	Watts
4005 (-P)	5,500	16w x 12h x 7d	16w x 13.7h x 8d	0.16	19.2
4005C (-P)	5,500	16w x 12h x 7d	16w x 13.7h x 8d	0.18	21.6
4005CS (-P)	5,500	16w x 12h x 7d	16w x 13.7h x 8d	0.23	27.6
4007 (-P)	7,500	16w x 12h x 7d	16w x 13.7h x 8d	0.15	17.5
4007C (-P)	7,500	16w x 12h x 7d	16w x 13.7h x 8d	0.15	18.0
4007CS (-P)	7,500	16w x 12h x 7d	16w x 13.7h x 8d	0.22	26.4
4030 (-P)	30,000	16w x 12h x 7d	16w x 13.7h x 8d	0.58	69.5
4030C (-P)	30,000	16w x 12h x 7d	16w x 13.7h x 8d	0.60	72.0
4030CS (-P)	30,000	16w x 12h x 7d	16w x 13.7h x 8d	0.65	78.0

4000C SERIES

Model	Description	Dimensions	Additional Amps	Additional Watts
4000CI(TR)	Touch Controller	6w x 6h x 4d	0.02	2.4
4000S	Sensor	6w x 6h x 4d	0.03	3.6



PROUDLY MADE IN THE USA



1865 Herndon Ave. Ste. K126 | Clovis, CA 93611
 T 855.201.SAGE | www.SAGEINDUSTRIAL.com